



Coaxial Cable Stripping Tool

DXE-UT-8213

For RG8, RG-213, LMR 400 coaxial cable

Patent Pending

DXE-UT-8213-INS Rev 1



The **DXE-UT-8213** has been designed to properly cut coaxial cable for use with PL-259 connectors.

The **UT-8213** has been tested with: Belden 8213 RG-11/U, Belden 8214 RG-8, Belden 8217, Belden 8267,

Belden 9913 RG-8 (spiral dielectric material), Belden 9913F7 RG-8 high-flex, Davis RF Bury Flex, and Times Microwave LMR-400 (not LMR-400/UF).

Properly cut the end of the coaxial cable with the **DXE-CNL-911** Coax Cable Cutter to get a good flush cut. You want the coax to be round and not oval when viewed from the end. If the cable is slightly oval, gently use pliers to round out the end of the coaxial cable. Place the prepared coaxial cable end into the body of the **UT-8213** labeled "**1st CUT**". Firmly grip the coaxial cable and the **UT-8213**, turn the **UT-8213** in a clock wise direction while applying steady and slightly firm pressure. The **UT-8213** will begin cutting. Keep turning the tool until it will not cut anymore, it will stop cutting at the proper length. Remove the coaxial cable, turn the **UT-8213** around for the second cut. Insert the coaxial cable into the tool and again, turn the tool in a clock wise direction until the cutting is complete. Remove the coaxial cable. Clean any excess cable cuttings from the tool. You may want to trim some of the braid on the coaxial cable slightly using the **DXE-170M** precision shear side cutters prior to installing in a PL-259 connector using the **DXE-UT80P** Connector Assembly Tool . This combination of DXE tools allows perfect and easy connector installation every time! The premium cutting blades supplied with the **UT-8213** will last a long time. If replacements are needed, order **DXE-UT-RB-HD** (customer supplied 7/64" Allen Wrench required).



1 - Cut Coaxial Cable



2 - Insert in "1st Cut" side



3 - Turn clockwise to make first cut



4 - First Cut Complete



5 - Insert in other side for 2nd cut, turn clockwise to cut



6 - Completed Coaxial Cable



Martin Lynch & Sons Ltd
Outline House
73 Guildford Street
Chertsey
Surrey
KT16 9AS

UK
Tel: 01932 567 333
Fax: 01932 567 222
Outside UK
Tel: +44 1932 567 333
Fax: +44 1932 567 222